

Eaton CH12L125B

Catalog Number: CH12L125B

CH 3/4-inch loadcenter, Main lug only, 125A, B, Copper, Ch8bf-combination, ch8bs-surface, NEMA 1, Metallic, Top/bottom, CH, 12, 12, Three-wire, Single-phase, 120/240V, #6-2/0 AWG



General specifications

Product Name	Catalog Number
Eaton CH main lug loadcenter	CH12L125B
UPC	Product Length/Depth
782113097374	16.75 in
Product Height	Product Width
3.88 in	14.31 in
Product Weight	Warranty
15 lb	Limited lifetime
Certifications	Catalog Notes
UL 50 UL 67	Suitable for use as service equipment when not more than six service disconnecting mains are provided or when not used as a lighting and appliance panelboard.

Product specifications

Number of spaces

12

Interrupt rating

25 kAIC

Phase

Single-phase

Wire size

#6-2/0 AWG

Bus material

Copper

Main circuit breaker

CH

Enclosure

NEMA 1

Amperage Rating

125 A

Enclosure material

Metallic

Type

Main lug only

Feed type

Top/bottom

Cover

Ch8bf-combination, ch8bs-surface

Number of wires

3

Number of circuits

12

Voltage rating

120/240 V

Box size

B

Resources

Brochures

[Type CH Circuit Breakers and Loadcenters](#)

[Loadcenters and Circuit Breakers](#)

Catalogs

[Eaton's Volume 1—Residential and Light Commercial](#)

Drawings

[Dimensional Drawing - CH 3/4 LOADCENTER, MAIN LUG ONLY, INDOOR NEMA 1, 120/240 VAC, 1 PHASE](#)

Installation instructions

[Cutler-Hammer Type CH and BR Loadcenters - Instructions](#)

Multimedia

[AFCI Educational Video](#)

Specifications and datasheets

[Eaton Specification Sheet - CH12L125B](#)



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com
© 2023 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)